



## PM5005 INTEGRATED AMPLIFIER



40 w x 2ch

CURRENT  
FEEDBACK

SYSTEM  
REMOTE

METAL  
FRONT

BUS

A-B

MM  
Phono

PURE  
DIRECT

green standby  
eco friendly

New to the Marantz collection, this excellent entry-level integrated amplifier breaks all the rules. That's because it's the first in its class to offer current feedback architecture – a feature that normally is reserved for the more expensive models. This technology provides very fast and accurate signal handling, which results in perfectly balanced stereo sound reproduction as well as a very open and precise sound stage. It's also been recently enhanced with performance-optimising discrete audio circuitry and fine-tuning components. In addition, this year's model looks a little more stylish than last year's, thanks to new elegant knob design. On top of that, it comes with a new remote and a new low-power stand-by and auto stand-by mode. But back to being an amp: the PM5005 offers 40W per channel into 8 ohm or 55W into 4 ohm, and includes a metal chassis and a front metal panel to ensure a very rigid and solid base. It also has a Phono MM equaliser, as well as a Source Direct functionality to ensure shortest signal paths. Without doubt, the PM5005 has raised the performance bar in the so-called entry level area. Great sound. Amazing versatility.

### Main Features

- Integrated Current Feedback Amplifier with 2x 40W / 8 ohm rms
- Gold Plated Inputs/Outputs incl. Phono (MM) input
- Marantz proprietary HDAM-SA3 circuits
- Selected high quality audio components
- Fully discrete volume amplifier circuit
- Tone control and Source Direct function
- High quality Speaker Terminals (A / B switchable)
- Headphone output
- System remote to control Amplifier, CD-Player and Network Player

### EAN

EU PM5005/N1B 4951035051146 Black  
PM5005/N1SG 4951035051139 Silver-Gold

[www.marantz.eu](http://www.marantz.eu)

# because music matters

## PM5005 INTEGRATED AMPLIFIER



| FEATURES                           | PM5005                  |
|------------------------------------|-------------------------|
| Channels                           | 2                       |
| Current Feedback Topology          | •                       |
| Phono EQ: Standard                 | •                       |
| HDAM version                       | SA3, SA2                |
| Toroidal Power Transformer         | •                       |
| High Grade Audio Components        | •                       |
| Balance / Bass / Treble / Loudness | • / • / • / •           |
| OTHERS                             |                         |
| Linear Drive Power Supply          | •                       |
| Source Direct                      | •                       |
| Standby Mode                       | •                       |
| INPUTS / OUTPUTS                   |                         |
| Audio Inputs                       | 6                       |
| Phono Input: MC                    | •                       |
| Audio Outputs                      | 2                       |
| Gold Plated Cinch                  | •                       |
| Speaker A / B                      | •                       |
| Speaker Terminals:                 | Transparent, Screw type |
| Number of terminals                | 4                       |
| D-Bus                              | •                       |
| Headphone Out                      | •                       |

| SPECIFICATIONS                        |                    |
|---------------------------------------|--------------------|
| Power Output (8 / 4 Ohm RMS)          | 40 W / 55 W        |
| Frequency Response                    | 10 Hz - 50 kHz     |
| Total Harmonic Distortion             | 0.05 %             |
| Damping Factor                        | 100                |
| Input Sensitivity: MM                 | 2.2 mV / 47 kOhm   |
| Signal to Noise Ratio: MM             | 83 dB              |
| Input Sensitivity: High level         | 200 mV / 20 kOhm   |
| Signal to Noise Ratio: High level     | 102dB (2V input)   |
| GENERAL                               |                    |
| Available colors: Black / Silver-Gold | • / •              |
| Metal Front Panel                     | •                  |
| Power Consumption                     | 110 W              |
| Standby Consumption                   | 0.3 W              |
| Auto Power off                        | •                  |
| Detachable Power Cable                | •                  |
| Remote Control                        | RC002PMCD          |
| System Remote Function                | •                  |
| Maximum Dimensions (W x D x H)        | 440 x 370 x 105 mm |
| Weight                                | 6.7 kg             |

Design and specifications are subject to change by Marantz without notice.

Perfect partner  
**CD5005**



CD Player